

DCN-CCU2 Central Control Unit

www.boschsecurity.com



BOSCH
Invented for life



- ▶ For DCN Next Generation or DCN wireless systems, or a combination of the two
- ▶ In single-CCU; maximum 245 wired contribution units, plus 245 wireless delegate units
- ▶ For multi-CCU systems, with up to 30 CCU's and a total of 4000 contribution units
- ▶ Voice activated microphone mode for wired and wireless systems
- ▶ Ethernet connection for configuration and control computers

The Central Control Unit (CCU) includes features for controlling wired and wireless delegate microphones, distributing simultaneous interpretation and conducting voting sessions, all without an operator. In combination with a PC, this control unit brings greater sophistication to conference control. Users can access an extensive range of software modules, each with a specific function in controlling and monitoring a conference. These modules greatly expand the capacity to manage a conference. In the event of PC failure, this control unit will revert to its stand-alone operation mode, enabling the conference to proceed.

Functions

- For DCN Next Generation or DCN wireless systems, or a combination of the two (Maximum one DCN-WAP per system)
- Basic microphone management facilities
- Four operational microphone modes:
 - Open: microphone button control with request-to-speak (Auto)
 - Override: microphone button with override of activated microphones (FIFO)
 - Voice: voice activated microphones
 - Push-to-talk (push and hold button to speak)
- Number of open microphones between 1 and 4
- Configuration of CCU and system via a display and a single rotary push button
- Basic voting control for parliamentary voting procedure. Delegates can register 'Present', 'Yes', 'No' and 'Abstain'. The Concentus Chairman unit can start, stop and suspend the voting. The total results can be displayed on hall displays and on the LCD screens of the units
- A page function which activates a voting tone. With this tone the chairman can indicate that a voting round is about to start
- Simultaneous interpretation function with 31 language channels plus one floor channel
- Distribution of up to 10 language channels plus floor to DCN wireless discussion units
- Distribution of up to 31 language channels plus floor to Integrus receivers, DCN wired channel selectors
- Basic intercom function with function to assign intercom operator and intercom chairman (both can be called from the interpreter desk)
- Stand-alone automatic camera control
- Extended conference facilities when using control PC software or remote controllers
- Adjustable sensitivity for the audio inputs
- Adjustable level for the audio outputs
- Audio insertion facility to connect external audio processing devices or telephone couplers

- The CCU can be assigned a unique name by the installer for easy identification
- VU meter readings to monitor audio inputs and audio outputs. The audio can be monitored using a headphone
- 19" (2U) housing for tabletop or rack mounting
- Handgrips for easy transportation

Controls and Indicators

Front

- Power on/off switch
- 2 x 16 Character LCD display for status information and configuration
- Rotary control to navigate through the LCD menus

Back

- Three red LED overload indicators for the DCN network outputs
- Two red LED overload indicators for the optical connections
- Green and yellow LED indicating Ethernet activity

Interconnections

Front

- One stereo headphone output 3.5 mm (0.14 in)

Back

- Euro power socket with built-in fuse
- Three DCN outlet sockets including locking facility for connection of units
- Two optical network connections for connection of Integrus, various audio expanders, CobraNet interfaces and Wireless Access Point
- Two three-pole XLR balanced audio line inputs with galvanic separation
- Two stereo Cinch unbalanced audio line inputs
- Two three-pole XLR balanced audio line output with galvanic separation
- Two stereo Cinch unbalanced audio line outputs
- One Ethernet connection for Control PC, Open Interface or slave CCU
- One RS-232 serial data connector for controlling cameras
- One error switch, galvanic separated cross-over switch to trigger external equipment in case of errors detected by the CCU

Certifications and approvals

Region	Certification
Europe	CE

Parts included

Quantity	Component
1	DCN-CCU2 Central Control Unit
1	Set of mounting brackets for 19" rack
1	Set of feet
1	System installation and user instruction on DVD
1	US power cord
1	Euro power cord

Technical specifications

Electrical

Supply voltage	100-240 Vac 50-60 Hz
Power consumption	360 W
DCN system supply	40 Vdc, max 85 W per DCN socket
Optical network supply	40 Vdc, max 65 W
Total power supply	320 W
RS-232 connection	1 x nine-pole Sub-D female socket
Frequency response	30 Hz - 20 kHz (-3 dB at nominal level)
THD at nominal level	< 0.5 %
Cross talk attenuation	> 85 dB at 1 kHz
Dynamic range	> 90 dB
Signal-to-noise ratio	> 87 dBA

Audio inputs

XLR nominal input	-12 dBV (+/- 6 dB)
XLR maximum input	+12 dBV
Cinch nominal input	-24 dBV (+/- 6 dB)
Cinch maximum input	+0 dBV

Audio outputs

XLR nominal output	-12 dBV (+6 / -24 dB)
XLR maximum output	+12 dBV
Cinch nominal output	-24 dBV (+6 / -24 dB)
Cinch maximum output	+0 dBV

Mechanical

Mounting	Tabletop or mounted in a 19" rack
Dimensions (H x W x D)	
for tabletop use, with feet	92 x 440 x 400 mm (3.6 x 17.3 x 15.7 in)
for 19" rack use, with brackets	88 x 483 x 400 mm (3.5 x 19 x 15.7 in)
in front of brackets	40 mm (1.6 in)
behind brackets	360 mm (14.2 in)
Weight	7.9 kg (17.5 lbs)
Color	Charcoal (PH 10736) with silver

Ordering information

DCN-CCU2 Central Control Unit

Controlling of delegate microphones, distributing simultaneous interpretation and conducting voting sessions.

Order number **DCN-CCU2**

Represented by:

Americas:

Bosch Security Systems, Inc.
12000 Portland Avenue South
Burnsville MN 55337, USA
Phone: +1-800-392-3497
Fax: +1-800-955-6831
audiosupport@us.bosch.com
www.boschsecurity.com

Europe, Middle East, Africa:

Bosch Security Systems B.V.
P.O. Box 80002
5617 BA Eindhoven, The Netherlands
Phone: + 31 40 2577 284
Fax: +31 40 2577 330
emea.securitysystems@bosch.com
www.boschsecurity.com

Asia-Pacific:

Robert Bosch (SEA) Pte Ltd, Security Systems
11 Bishan Street 21
Singapore 573943
Phone: +65 6571 2808
Fax: +65 6571 2699
apr.securitysystems@bosch.com
www.boschsecurity.asia

China:

Bosch (Shanghai) Security Systems Ltd.
201 Building, No. 333 Fuquan Road
North IBP
Changning District, Shanghai
200335 China
Phone +86 21 22181111
Fax: +86 21 22182398
www.boschsecurity.com.cn

America Latina:

Robert Bosch Ltda Security Systems Division
Via Anhanguera, Km 98
CEP 13065-900
Campinas, Sao Paulo, Brazil
Phone: +55 19 2103 2860
Fax: +55 19 2103 2862
al.securitysystems@bosch.com
www.boschsecurity.com