



DCN-WCH05 Charger for 5 Battery Packs



- ▶ Simultaneous charging of up to 5 battery packs
- ▶ Recharges from empty in 3 hours
- ▶ Loop-through mains connector
- ▶ Auto-ranging PSU, 100 – 240 VAC

This unit can simultaneously re-charge up to 5 DCN-WLIION battery packs. The charging status of each pack is shown on individual charge capacity indicator LEDs.

The unit is suitable for tabletop use, or can be wall-mounted.

The loop-through mains voltage connector allows a maximum number of charging units to be connected in series to share from the same mains outlet:

- A maximum 5 chargers can be connected in series for 100 - 127 VAC, 50 - 60 Hertz regions
- A maximum 10 chargers can be connected in series for 220 - 240 VAC, 50 - 60 Hertz regions

Functions

Controls and Indicators

- Charge capacity indicator LEDs on each bin
- Mains power indicator LED

Interconnections

- Mains supply connector
- Loop-through mains connector
- Battery pack charging connector

Technical Specifications

Electrical

Supply Voltage	100 - 240 VAC +/- 10 % 50 - 60 Hz
----------------	--------------------------------------

Maximum power consumption	190 W
---------------------------	-------

Mechanical

Dimensions (H x W x D)	340 x 195 x 82 mm (13.4 x 7.6 x 3.2 in)
------------------------	---

Weight (without batteries)	1.4 kg (3.08 lb)
----------------------------	------------------

Color	Charcoal (PH 10736)
-------	---------------------

Ordering Information

DCN-WCH05 Charger for 5 Battery Packs

DCN-WCH05

Americas:
Bosch Security Systems, Inc.
130 Perinton Parkway
Fairport, New York, 14450, USA
Phone: +1 800 289 0096
Fax: +1 585 223 9180
security.sales@us.bosch.com
www.boschsecurity.us

Europe, Middle East, Africa:
Bosch Security Systems B.V.
P.O. Box 80002
5600 JB Eindhoven, The Netherlands
Phone: + 31 40 2577 284
Fax: +31 40 2577 330
emea.securitysystems@bosch.com
www.boschsecurity.com

Asia-Pacific:
Bosch Security Systems Pte Ltd
38C Jalan Pemimpin
Singapore 577180
Phone: +65 6319 3450
Fax: +65 6319 3499
apr.securitysystems@bosch.com
www.boschsecurity.com

Represented by